BRIGGS & STRATTON 2400A

PORTABLE GENERATOR FOR HOME USE

FEATURES:

- Briggs & Stratton Intek™ I/C® engine
- Automatic Voltage Regulator (AVR)
- · Circuit breaker protected
- Full protection cradle
- Voltmeter
- Cradle mounted outlet panel
- Low oil shutdown system
- Warranty 2 years



SPECIFICATIONS

BRIGGS & STRATTON 2400A

Rated Power [W]	2000
Equivalent Max. kVA*	2.5
Engine Type / HP**	Intek™ I/C® OHV
Fuel Capacity [L]	3.8
Weight [kg]	40
LxWxH[cm]	56 x 45 x 42
Run Time @ 50% load	3h 45min
Consumption @ 50% load	1 l/h
Low oil shutdown protection system	Yes
Noise level LwA / dB at 7m	97 / 72
Circuit breaker	Yes
Wheelkit	No
Voltage / Frequency	230 V / 50 Hz
Туре	Export



Dashboard includes a voltmeter. 1 socket and a circuit breaker.



Briggs & Stratton Intek™ I/C OHV engine.














the power rating. This figure is for comparison with these values.

** All power levels are stated gross horsepower per SAE J1940 as rated by Briggs & Stratton.